

**DESCRIPTION**

The Q-N8000LC is an accessory adapter for N-8000RS or N-8010RS, N-8000 Substation Interface Unit, which converts the output signal of the interface unit into a line level audio signal or a 25V line speaker output. It is equipped with four channel outputs with level selection switch, which allows individual level adjustment for each channel.

**SPECIFICATIONS**

Number of Channel	4 channels
Connectors	Input: Eurostyle terminal connector (3pin) x4 Output: Removable terminal (3pin) x4 (Connectors are supplied with N-8000/8010RS)
Signal Adjustment	Three-position slide switch x4
Output Signal	"SP": Speaker Output (1w@25V) "RS": Bypass Output (Original N-8000/8010RS signal) "LN": Line Level Output (+9dBV max.)
Dimensions	2.72"(w) x 1.54"(h) x 1.10"(d)* (69 x 39 x 28mm*) *Not including output connectors.
Weight	1.09 oz (31g)

**APPEARANCE**
